



Switch & Lite Pro Multi-function Wireless Controller Specification

Product Features:

This product is specially designed for Switch & Lite console, which has unique appearance and various personalized colors.

1. Compatible with Console: Switch / Lite / Android phone, TV, TV box and other Android devices / Windows (PC) / PS3
2. Bluetooth Mode: Switch / Lite / Android Phones, TVs, TV Boxes and other Android devices
Wired Mode: Switch / PS3 / PC
- 2.4G Wireless: Support Android (for devices without Bluetooth) / PC;
(Note: 2.4G receiver needs to be purchased separately)
3. Built-in 6-axis somatosensory chip
4. Built-in motor vibration function
5. Support independent TURBO / combo button
6. Button function corresponds to SWITCH PRO controller
7. Support hibernation and one-key connection
8. Cute shape and personal color design

Product Parameters:

1. Color: Black/Blue/Yellow HS-SW532

2. Product Parameters:

Product Size: 147*98*55 mm

Product Weight: 0.208kg

Product Material: ABS

Product Color: Black/Blue/Yellow

3. Electrical Parameters:

Compatible with Console	Switch & Lite / PC / PS3 / Android
Operating Voltage	DC3.7-4.2V
Charging Voltage and Current	DC4.5-5.5V / 400mA



Input Interface	TYPE C
Working Current	20-150mA
Bluetooth Transmission Distance	≅ 8M
Battery Capacity	600mAh
Sleep Current	<80μA
Charging Time	About 3 Hours
Standby Time	3 Months

4. Packaging Parameters:

Single Packing Weight:0.300 kg

Color Box Size:166*132*65 mm

Packing Quantity: set / box

Packing Size:

Gross Weight:

5.Information: Specification

6. Operating Instruction

1.) Connection

Console	Bluetooth Connection	Wired Connection
SWITCH	Press and hold HOME5s to pair	Connect the original dock through the data cable
PC	NOT Support	Connect to the console through the data cable(the default Xinput) and long press the screenshot button 2S to switch to Dinput
Android	Press HOME + Y 2s to pair	NOT Support
PS3	NOT Support	Hold down the L1 key to connect the USB cable and press HOME to pair



2.) TURBO Function

- Action keys include (A / B / X / Y / L / ZL / R / ZR) 8 keys, which can be set the TURBO function manually;
- Setting method: long press the action button then press the TURBO button to turn on; long press the action button then press the TURBO button and the TURBO function is turned off.
- Please note TURBO function is automatically cleared when the controller in dormant or closed or restart. If the TURBO function is enabled, it must be reset.

3.)Controller Sleep / Wake / Shutdown Function:

- When the console screen closed or no key operation within 5 minutes,the controller will automatically shut down to sleep;
- In the power-on state, press and hold the HOME button for 5 seconds then the product shuts down and all LED indicators turn off;
- When you need re-use, you just need lightly press the HOME button to wake up to connect back;
For other calibration functions, please check the instruction manual.

Product Pictures:

