



## SWITCH PRO Wireless (Bluetooth) Controller Specification

### Product Features:

1. Suitable for console: SWITCH
2. Unique shape, asymmetrical joystick design, four indicator lights, Decorative color strip & analog joystick have red and blue optional.
3. Wireless Bluetooth connection range 8 meters.
4. 6-axis gyroscope for a better gaming experience
5. Provide 16 function input buttons, support TURBO burst and burst elimination function
6. Built-in powerful vibration dual motor, 256-level precision 3D joystick
7. Support analog joystick, six-axis calibration
8. The ergonomic design and lightweight controller construction make the player feel comfortable and will not feel tired even if they play continuously.
9. One-button RESET design
10. No need to load any drive, the controller can be used after pairing with the console .
11. Non-slip grip design
12. Low voltage alarm/sleep
13. TYPE-C interface with 0.7 m USB cable
14. 500mAh rechargeable lithium battery, support long game

### Product Parameters:

1. **Red and blue color optional:** decorative strip analog joystick

#### 2. Controller parameters:

Controller Size: 157\*110\*57mm

Controller Weight: 0.220kg

Material: ABS

Color: Upper cover (black) + lower cover (black) + decorative strip analog joystick  
(blue / red) + button (black) color optional

Button Silk printing: White ABXY



### 3.Electrical parameters:

Input voltage:	DC 4.5-5.5V
Input current:	400mA
Operating Voltage:	DC 3.7V
Operating current:	20mA-150mA
Battery:	Built-in polymer lithium battery
Battery capacity:	500mAh
Battery Operating time:	6-10 hours (Operating time depends on different time)
Charging time:	2.5 hours
Charging current:	< 350mA
Charging interface:	TYPE-C
USB charging cable:	0.7m
Bluetooth version:	2.1+ED

### 4. Packaging Parameters:

Single package weight: 0.310kg  
Color box size: 175x135x65mm  
Packing quantity: 40 sets / box  
Packing size: 570\*345\*370mm  
Gross weight: 12.8kg

**5.Information:** Packing documents (there are some indicators in this package are incorrect, subject to the manual and this specification), Instruction manual

### Product Pictures:

